LIGHTING >lunix

aIRSTaR

lunix

technical data

Sphere



Lunix CX



Diamond



Diamond with cubic slip cover



	Lunix 200	Lunix CX	Lunix 250	Lunix 300	Lunix 370	Lunix 500
Size	6.5 ft	6.5 x 8 ft	8 ft	10 ft	12 ft	16 ft
Helium tanks (291 cft)	1	2	2	2	5	10
Average set up time	15 min		20 min		30 min	45 min
Light source	Halogen					
Voltage	120 v / 220 v				120 v / 220 v	
Power (Halogen)	4 x 650 W / 4 x 1,000 W		4 x 650 W / 4 x 1,000 W		8 x 650 / 8 x 1,000 W	Up to 20,000 W
Lumens	up to 48,000 lm				96,000 lm	Up to 192,000 lm
Wind resistance	15 mph		20 mph			25 mph

AIRSTAR

LIGHTING

Airstar is the inventor and leading manufacturer of innovative balloon lighting for all types of events.

Airstar America Inc.
Tel: 1 (800) 217-9001
www.airstar-light.us